

## 6.730 PHYSICS FOR SOLID STATE APPLICATIONS

Department of Electrical Engineering and Computer Science  
Massachusetts Institute of Technology

### PROBLEM SET 7

Issued: 4-27-01

Due: 5-9-01, at the beginning of class.

**Problem 7.1** Total Conductivity Tensor for bulk Si.

The 6 constant energy surfaces for energies just above the conduction band edge in silicon are shown below.

These surfaces are ellipsoidal and are described by two effective masses;  $m_t$  for the transverse mass and  $m_\ell$  for the longitudinal mass. For example, for the ellipsoid along the  $z$ -axis, the surface of constant energy is

$$E(\mathbf{k}) = E_c + \frac{\hbar^2}{2} \left( \frac{(k_x - k_{x,0})^2}{m_t} + \frac{(k_y - k_{y,0})^2}{m_t} + \frac{(k_z - k_{z,0})^2}{m_\ell} \right).$$

(a) The acceleration  $\mathbf{a}$  response to an external driving force  $\mathbf{F}$  is given in terms of the the inverse of the effective mass tensor  $\mathbf{M}_j^{-1}$  for each pocket  $j$ ; namely,  $\mathbf{a}_j = \mathbf{M}_j^{-1} \mathbf{F}$ . Show that the total acceleration responds isotropically

to the force; that is,  $\mathbf{a}_{\text{total}} = M^{-1}\mathbf{F}$ , where  $M$  is a scalar. Be sure to calculate the contributions from all six ellipsoids and find  $M$  explicitly.

(b) What is the numerical value of this effective mass ratio  $M/m_e$  for Si.

(c) Refer to part (a) and write out the total effective mass tensor for the conductivity of electrons in Si explicitly.

(d) Do the same for the holes, assuming; that there are two hole bands with different effective masses. Also give a numerical value for the effective (conductivity) mass ratio for the holes in Si.

**Problem 8.2** Conductivity Tensor for a 2DEG in Si.

The electrons in the conduction band of Si are subjected to a slowly varying potential caused by band bending. Model this potential as

$$V(\mathbf{r}) = \frac{1}{2}m_3\omega_o^2z^2 \quad \text{for} \quad z \leq 0$$

where  $\omega_o$  is a positive constant of dimensions of inverse seconds.

(a) Use the Effective Mass Theorem to find the total energy of a wave packet near the bottom of the conduction band for each of the 6 ellipsoids. (To simplify the problem, assume that  $m_3$  “adjusts” itself so that the mass is the mass along the  $z$ -axis for each of the ellipsoids. This way the characteristic frequency does not change for the harmonic oscillator part of each ellipsoid.)

(b) Let all the electrons be in the first subband so that they form a two dimensional electron gas (2DEG). If the electric field is confined in the  $xy$ -plane, find the corresponding conductivity tensor.

(c) What is the numerical value for this effective mass for Si. How does it compare with that in Problem 7.1 for the full 3d conductivity effective mass and for the effective masses for 3D and 2D density of states?

**Problem 7.3** Auger Recombination.

A three-particle recombination process is described as follows

electron 1 + electron 2 + hole  $\implies$  one energetic electron

In effect, the other or “Auger” electron carries off the necessary momentum and energy required for an electron and hole to recombine in an indirect gap material.

Assume that the recombination rate is of the form  $R = An^2p$  where  $A$  is a constant.

Write the rate equation for the hole concentration, including both the generation and recombination terms, and show that for n-type material in low-level injection, the lifetime of excess carriers is  $\tau_p = 1/An_0^2$ , where  $n_0$  is the equilibrium carrier concentration.

**There will be no class on Wednesday May 2, 2001 and Friday May 4, 2001.**